

## Laptop Docking Module for Conference Table Connectivity Box

**Product ID:** MOD4DOCKACPD



Add docking and video conferencing capabilities to a boardroom, classroom or huddle space. This laptop docking module for the StarTech.com conference table connectivity box lets you:

- Access your room's display and collaboration peripherals with a single connection
- Charge mobile devices using the USB-A charge port
- Power a supported USB-C laptop with USB Power Delivery

Modern office environments need to support technology more than ever, to keep laptops, phones and tablets connected. During meetings, you may need to set up video conference calls using applications such as Microsoft Teams, Zoom or Google Hangouts. Unlike other boardroom conferencing solutions that are limited to only one or two collaboration applications, this module lets you use your own laptop, so you are not restricted to a specific platform.

Connect a USB-C or USB-A laptop to the module and access your room's peripherals, webcams, speakers, mics, network and HDMI display. This docking station module lets you easily connect your laptop with each video conferencing device in your boardroom. You can collaborate with others in the room and around the globe.

For users that are unable to dock or for quick access to the display, the front-facing HDMI port lets you connect a laptop directly to the display.

Architectural connectivity is becoming the trend when designing a boardroom or huddle space. StarTech.com docking station modules let you:

- Customize according to the specific needs of your small, medium or large size room
- Install in easy-to-access locations
- Easily integrates with existing and new collaboration hardware

You can install this module as a standalone solution using the supplied table-mounting bracket, or as an addition to a StarTech.com single-module (BEZ4MOD) or dual-module (BOX4MODULE) conference room table connectivity box

(each sold separately).

Developed to improve performance and security, StarTech.com Connectivity Tools is the only software suite on the market that works with a wide range of IT connectivity accessories. The software suite includes:

Advanced Windows Layout Utility: To setup and save custom windows layouts.

Mac Address Pass-Through Utility: To improve network security.

USB Event Monitoring Utility: To track and log connected USB devices

Wi-Fi Auto Switch Utility: Enabling users to quickly access faster network speeds via wired LAN.

For more information and to download the StarTech.com Connectivity Tools application, please visit:  
[www.StarTech.com/Connectivity-Tools](http://www.StarTech.com/Connectivity-Tools)

MOD4DOCKACPD is backed by a StarTech.com 2-year warranty and free lifetime technical support.

## Certifications, Reports and Compatibility



## Applications

- Add docking station connectivity to the BOX4MODULE or BEZ4MOD
- Simple connectivity between your laptop and your room's devices
- Perfect for conference calls and presentations
- Ideal for meeting rooms, classrooms, and huddle spaces
- Install as a standalone solution in a workbench or lectern

## Features

- Easily access boardroom or huddle space devices and set up conference calls using applications such as Skype for Business

- Connect to all your boardroom peripherals from a USB-C or USB-A laptop
- Power and charge your USB-C laptop with USB Power Delivery 2.0 (up to 60W)
- Keep your mobile devices charged with the USB-A charging port
- Use as a standalone solution or combine with a single-module or dual-module StarTech.com Connectivity Box
- CONNECTIVITY TOOLS: Provided with this device, the application improves performance and security, featuring MAC Address Changer, USB Event Monitoring, Windows Layout & Wi-Fi Auto Switch utilities

---

## Hardware

Warranty	2 Years
4K Support	Yes
Fast-Charge Port(s)	Yes
Displays Supported	1
Bus Type	USB-C
	USB 3.2 Gen 1 (5Gbps)
Industry Standards	USB Power Delivery Specification Rev. 2.0
	USB Battery Charging Specification Rev. 1.2
	IEEE 802.3, IEEE 802.3u, IEEE 802.3ab
	USB 3.0 - Backward compatible with USB 2.0 and 1.1
Chipset ID	DisplayLink - DL-6950
	Genesys Logic - GL850G
	Texas Instruments - TPS65982
	Parade Technologies - PS176
	VIA Labs - VL813
	Realtek - RTL8153

---

## Performance

Maximum Data Transfer Rate	5 Gbps (USB 3.0)
	2 Gbps (Ethernet; Full-Duplex)
Maximum Digital Resolutions	3840 x 2160p (4K) @ 30Hz

Type and Rate	USB 3.0 - 5 Gbit/s
UASP Support	Yes
Compatible Networks	10/100/1000 Mbps
Auto MDIX	Yes
Full Duplex Support	Yes

---

#### Connector(s)

Connector Type(s)	3 - HDMI (19 pin)
	1 - USB 3.2 Type-A (9 pin, Fast-Charge)
	3 - USB Type-A (9 pin, 5 Gbps)
	2 - 3.5 mm Mini-Jack (3 Position)
	1 - RJ-45
	1 - USB 3.2 Type-C (24 pin, Gen 1, 5Gbps)
	1 - USB 3.2 Type-B (9 pin, Gen 1, 5Gbps)

---

#### Software

OS Compatibility	Windows 7, 8, 8.1, 10, 11
	macOS 10.9 - 10.12, 10.14 - 10.15, 11.0, 12.0, 13.0
	Chrome OS v55+

---

#### Special Notes / Requirements

Note	<p>Not all USB-C ports support the full functionality of the USB Type-C standard. Ensure that your host USB-C port supports USB Power Delivery 2.0 and DP alt mode.</p> <p>4K resolution is supported. A 4K-capable display is required to achieve 4Kx2K resolution</p> <p>If connected to a USB 2.0 host port, or if using a USB 2.0 host connection cable, performance may be limited (USB 3.0 host cable included)</p> <p>USB 3.0 is also known as USB 3.1 Gen 1; this connectivity standard offers speeds up to 5Gbps</p> <p>The dock connects to the USB-C port on your laptop. The dock can also be connected to the USB-A port on laptops using a USB-B to A cable (included), but Power Delivery to charge your laptop is not available through USB-A</p>
------	---

DisplayLink drivers are required for connecting your USB-A laptop to the USB-B port on the module. If your laptop doesn't have the proper drivers installed and you're unable to download and install the drivers, you can connect your laptop directly to the HDMI port to access the room's HDMI display.

---

**Indicators**

LED Indicators	1 - Power
----------------	-----------

---

**Power**

Power Source	AC Adapter Included
Power Delivery	60W
Input Voltage	100 - 240 AC
Input Current	2 A
Output Voltage	20V DC
Output Current	6 A
Center Tip Polarity	Positive
Plug Type	N
Power Consumption (In Watts)	120W

---

**Environmental**

Operating Temperature	0C to 40C (32F to 104F)
Storage Temperature	-20C to 65C (-4F to 149F)
Humidity	20~80% RH

---

**Physical Characteristics**

Color	Black
Material	Aluminum and Plastic
Product Length	4.7 in [12.0 cm]
Product Width	3.7 in [9.4 cm]
Product Height	2.4 in [6.1 cm]

Weight of Product	20.8 oz [588.0 g]
-------------------	-------------------

---

**Packaging Information**

Package Quantity	1
Package Length	9.9 in [25.1 cm]
Package Width	8.3 in [21.1 cm]
Package Height	0.4 in [1.0 cm]
Shipping (Package) Weight	4.6 lb [2.1 kg]

---

**What's in the Box**

Included in Package	1 - docking station module
	1 - universal power adapter
	3 - power cords (NA, EU, UK)
	1 - USB-A to USB-B cable
	1 - USB-C cable
	1 - mounting bracket
	4 - mounting bracket screws (M5 x 20 mm)
	8 - module screws (#6-32 x 3/16")
	1 - quick-start guide

---

***\*Product appearance and specifications are subject to change without notice.***